



TECHNICAL INFORMATION

TITLE: SE-601 DC GROUND-FAULT PROTECTION

The SE-601 is a microprocessor-based ground-fault monitor for ungrounded dc systems. Ground-fault current is sensed by monitoring a voltage-reference point established with the SE-GRM.

When there is no ground fault, 12 mA of current will flow through the SE-GRM. When a ground fault occurs, ground-fault current will flow through the ground to the SE-601, through internal 25-Ω resistance in the SE-601, to the S terminal, and through the SE-GRM to the unfaulted line (refer to Fig. 2). The resistance of the SE-GRM will limit the ground-fault current to a maximum of 25 mA. The SE-601 has a digital-switch selectable ground-fault current trip range from 1 to 20 mA, and a digital-switch selectable trip delay time range of 50 ms to 2.5 s. The SE-601 will trip when the ground-fault current exceeds the selected settings.




FIGURE 1. Unfaultered System

DATE	REV	AUTHOR	DOCUMENT LOCATION	PAGE
2003-Nov-17	0	TK	http://www.startco.ca/library/techinfo/section10/10.7.pdf	1 of 2



TECHNICAL INFORMATION

TITLE: SE-601 DC GROUND-FAULT PROTECTION




FIGURE 2. Faulted System

TABLE 1. SE-601 Trip Levels and Fault Values

SE-601 TRIP LEVEL (mA)	FAULT RESISTANCE (Ω)
1	60 k
2	29 k
3	18 k
4	13 k
5	10 k
6	7.9 k
8	5.3 k
10	3.7 k
15	1.6 k
20	600